

## PDSEGEN Reference Card

Primary Commands	
Command	Description
<b>BACKUP</b>	Backup PDSE V2 member generations
<b>BROWSE</b> <i>member</i>	Browse member
<b>C</b> <i>dsn filter</i>	Change to another PDSE, with mbr filtering
<b>COPY</b> <i>dsn</i>	Copy to a PDSE
<b>EDIT</b> <i>member</i>	Edit member
<b>FILTER</b>	Member list filtering
<b>FIND</b> <i>text</i>	Find a text string in member name or data
<b>GENONLY</b>	Only non-0 generations
<b>HIDE</b>	Only 0 generations
<b>HIGEN</b>	Information on deleted members
<b>INFO</b>	Dataset summary information
<b>LOCATE</b> <i>text</i>	Locate text string
<b>MODEL</b>	Allocate new PDSE with same attributes
<b>MONTH</b>	Members changed in last 30 days
<b>OPTIONS</b>	Display and execute all primary commands
<b>OUTPUT</b>	Write member list to dataset
<b>PRUNE</b>	Delete all non-generation members
<b>REFRESH</b> or <b>RESET</b>	Rebuild member list
<b>RESTORE</b>	Restore members from backup DSN
<b>TODAY</b>	Members changed today
<b>VALIDATE</b>	Validate PDSE dataset
<b>WEEK</b>	Members changed in last 7 days
<b>VIEW</b> <i>member</i>	View member
<b>YEAR</b>	Members changed this year

Line Commands		
Command	Only	Description
<b>A</b>	Zero	Attribute of member
<b>B</b>		Browse member
<b>C</b> or <b>COP</b>	Zero	Copy member, with generations
<b>D</b>		Delete member
<b>E</b>	Zero	Edit member
<b>G</b> or <b>REC</b>	Non-Zero	Recover a generation to a new member
<b>H</b>		Hide member
<b>I</b>		Information on member
<b>J</b>		Submit member
<b>K</b>	Zero	Copy member
<b>M</b>		Mail member
<b>O</b>		Options
<b>P</b>	Non-Zero	Promote non-zero generation to zero
<b>Q</b> or <b>RENS</b>	Zero	Swap two member names and gens
<b>R</b> or <b>REN</b>	Zero	Rename member
<b>S</b>		Select member (B, E or V)
<b>U</b>		Enter user command
<b>V</b>		View member
<b>X</b>		Execute member
<b>Z</b> or <b>COM</b>	Non-Zero	Compare non-zero generation to zero

Comments	
Primary Commands	Line Commands
Primary command characters <u>underlined</u> and <b>bold</b> signify abbreviation	Placing the cursor on a row and pressing <b>ENTER</b> will select the member
Wild cards (%) and (*) can be specified in the member name	Line commands can be blocked or numeric, example: <b>DD-DD</b> or <b>D9999</b>
Type <b>LEFT (F10)</b> or <b>RIGHT (F11)</b> to display different columns	The 'Status' field allows typing in a member name for some commands
Type <b>HELP (F1)</b> to display tutorials	Several line commands can be typed in at once